

HF MULTIVOLTAGE: IGBT/THREE-PHASE

Model	Voltage From 12 V to ...	Current From 0 A to ...	Max battery capacity	Cable section mm ²	REF
IGBT3	24 V	120 A	1050 Ah	35	<u>139TA2728</u>
IGBT4	24 V	200 A	1700 Ah	70	<u>140TA7501</u>
IGBT14	24 V	250 A	2125 Ah	95	<u>140TA7503</u>
IGBT5	36 V	120 A	1050 Ah	35	<u>139TA2729</u>
IGBT6	36 V	200 A	1700 Ah	70	<u>140TA7502</u>
IGBT15	36 V	250 A	2125 Ah	95	<u>140TA7504</u>
IGBT20	36 V	320 A	2720 Ah	95	<u>140TA7508</u>
IGBT50	36 V	500 A	4250 Ah	-	<u>140TA7511</u>
IGBT7	48 V	120 A	1050 Ah	35	<u>139TA2730</u>
IGBT11	48 V	200 A	1700 Ah	70	<u>139TA2731</u>
IGBT18	48 V	250 A	2125 Ah	95	<u>140TA7505</u>
IGBT30	48 V	320 A	2720 Ah	95	<u>140TA7509</u>
IGBT45	48 V	400 A	3400 Ah	120	<u>140TA7510</u>
IGBT55	48 V	500 A	4250 Ah	-	<u>140TA7512</u>
IGBT9	80 V	120 A	1050 Ah	35	<u>139TA2732</u>
IGBT13	80 V	200 A	1700 Ah	70	<u>139TA2733</u>
IGBT19	80 V	250 A	2125 Ah	95	<u>140TA7506</u>
IGBT40	80 V	320 A	2550 Ah	95	<u>139TA2734</u>